



The Best Generator for Your Camping Adventure!

More and more Australian's are spending their holidays enjoying the great outdoors. No matter if you love tenting, or the luxury of a caravan a petrol generator can help make your trip a lot more comfortable. Looking for a generator to power all your appliances on your trip away....this is it!

**MX2800ISE** 

Barcode: 936905000425



## 2800W Pure Sine Wave Digital Inverter Generator













- · Digital inverter technology
- Pure sine wave power for sensitive electronic appliances / devices
- · Parallel connection cable included
- Low noise 65db
- 5V 2.1 Amp USB charging
- Engine smart control reduces engine speed depending on size of load for fuel efficiency
- Quick release telescopic handle and wheels for easy transportation



## Technical Information

Voltage (V)	240V
Amperage (A)	11.67A
Displacement (cc)	149cc
Fuel Tank Capacity (L)	7L
Rated Power (Watts)	2500W
Max. Power (Watts)	2800W



Double your power by connecting 2 generators in parallel

_	
Noise Level (dB's) at 7m @ 75% Load	65
Weight (Net)	28kg
Ignition	Electric / Recoil
Rated Frequency	50Hz
Cont. Running Time @50% Load	8.5 hrs
Cont. Running Time @100% Load	5.5 hrs

Generator Dimensions Length 500mm | Width 310mm | Height 480mm | Weight 28kg

Box Dimensions Length 540mm | Width 350mm | Height 540mm | Weight 30kg