

LEISURE GENERATORS

MX2000ISR 2000W Recoil Start Digital Inverter Generator

Power Your Adventure - Anywhere You Roam

For adventurers, campers, and caravan owners exploring off-grid destinations, portable power is essential. That's where our camping and caravan generators come in—designed to keep your favourite travel comforts running smoothly, no matter how remote the location.

Not all generators are built for life on the move. With years of experience supplying portable power solutions to travellers, we've identified the key features to look for when choosing the right generator for your camping or caravanning lifestyle.

TECHNICAL INFORMATION

Voltage:	240V
Amperage:	7.5A
Displacement:	79.7cc
Engine Speed:	3300-5000rpm
Outlets:	2 x 15A IP66
Covered Outlets:	5V DC USB / 2-wire Connect
Rated Power:	1800W
Max Power:	2000W
Starting Method:	Recoil
Noise Level:	60dB
Fuel Tank:	4.2L
Rated Frequency:	50Hz
Cont Running Time @ 50% Load:	7 hours
Cont Running Time @ 100% Load:	4 hours
Generator Dimensions (LxWxH):	485 x 290 x 440mm
Net Weight:	18.5kg

