

# WORKSITE GENERATORS

## MX13000AS

13kVA / 11000W  
Electric Start Petrol Generator

### Power You Can Rely On, Built for the Jobsite

Our worksite generators are engineered with tradies in mind - delivering the durability, reliability, and performance today's demanding job sites require.

Built to withstand harsh conditions, these generators offer consistent power, fuel efficiency, and easy maintenance, all backed by responsive on-site support.

Whether you're running heavy equipment or essential tools, our generators keep your site powered and your project on schedule.



### TECHNICAL INFORMATION

Voltage:	240V
Amperage:	43.8A
Displacement:	688cc
Engine Speed:	Constant 3600 rpm
Outlets:	2 x 15A IP66 / 1 x 32A IP66
Rated Power:	10000W
Max Power:	11000W
Starting Method:	Electric / 2 Wire Auto Start
Noise Level:	96dB
Fuel Tank:	45L
Rated Frequency:	50Hz
Battery:	12V 36Ah Lead Acid
Fuel Running Time @ 50% Load:	10 hours
Fuel Running Time @ 100% Load:	6 hours
Generator Dimensions (LxWxH):	730 x 600 x 780mm
Net Weight:	167kg

